

description

The TOTEABLE is a small tote bag with a personal FM receiver and a built-in speaker amplifier, which turns any desktop into a mini sound field system. It has a pocket on the back for storage and a wrist strap and shoulder strap for easy carrying.

application

Used in small groups or by students with cochlear implants, AD/HD, APD, or minimal hearing loss; also useful for reinforcement of ESL instruction.

key features

- Uses EASY LISTENER or SOLARIS receiver
- Small and lightweight
- Durable nylon exterior
- Simple operation
- Fully rechargeable

specifications: toteable sound field system



toteable sound field: 723A



user controls	off/on/volume (PE 300R/572R/575R)
inputs	charge jack
battery life (with 300R/350R)	53 hours with volume @ 5 29 hours with volume @ 7 7 hours with volume @ 9 (maximum)
battery type	4 rechargeable NiMH AA 1600mAH (included)
frequencies	72-76MHz & 173MHz
acoustical frequency response range	100Hz - 12kHz
maximum acoustical power output	86dBA @ 1/2m
range (with 300T & 300R)	9 to 15 m / 30 to 50 ft
dimensions (WxHxD)	18 x 15 x 10 cm / 7 x 5.5 x 4 in
weight	0.8kg/1.75lb
color	black

compatible with other units

electrical response with Easy Listener (300T or 300R)

power output	700mW pk
frequency response	100Hz to 10kHz
signal-to-noise ratio	> 56dBA @ 1kHz
dynamic range	> 56dBr @ rated output
THD	< 4% at rated output, 1kHz


electrical response with Solaris (571T, 572R or 575R)

power output	330mW pk
frequency response	100Hz to 10kHz
signal-to-noise ratio	> 45dBA @ 1kHz
dynamic range	> 40dBr @ rated output
THD	< 2% at rated output, 1kHz


Compatible with
EASY LISTENER and
SOLARIS 572R, 575R
receivers – just plug it
in and go!



optional accessories



AT0842/AT0837
two-unit charger



AT0799
adapter cord for SOLARIS
receivers 572R, 575R